

	<b>Tellus (i)6</b>	<b>Tellus (i)5</b>	<b>Vibe 12</b>	<b>Vibe</b>	<b>Mobi 3</b>	<b>Zingui 2</b>	<b>Smart 3</b>
Processor	Intel i5-8265U	Intel i5-4300U	Intel i5-1035G4	Intel N5000	Intel N3710	Tegra 2	Tegra 2
RAM	8Gb	4Gb, option 8Gb	8Gb	4 Gb	4 Gb	512 Mb	512 Mb
Storage	SSD 500 Gb	SSD 250 Gb	SSD 256 Gb	SSD 128 Gb	SSD 250 Gb	32 Gb	1 Gb
OS	Win10/11Pro x64	Win10Home x64	Win10/11Pro x64	Win10/11Pro x64	Win10LTSB x64	Windows CE	Windows CE
Display	14" 1920x1080	13.3" 1280x800	12.3" 2736x1824	10.1" 1920x1200	12" 1024x768	8" 800x480	4.3" 480x800
Touchscreen	capacitive	capacitive	capacitive	capacitive	capacitive resistive	capacitive	resistive
Second display	4" 256x64 white	–	3.12" 256x64 green	3.12" 256x64 green	–	–	–
WiFi	yes	yes	yes	yes	yes	–	–
BlueTooth	5.1	4.2	5.0	4.2	4.2	yes	yes
USB ports	1x USB/1x USB-C (USB 3.2 gen1)	3x USB 2.0	1x USB-C (USB 3.2 gen2)	1x USB-C (USB 3.2 gen1)	2x USB 2.0	1x USB OTG	1x USB OTG
Front cam	5MP	2MP	5MP	2MP	2MP (capacitive screen only)	–	–
Rear cam	13MP tilt cam	–	8MP	5MP	5MP (option)	2MP	2MP
ECU	IR, Z-Wave	IR (option)	IR, Z-Wave (option)	–	IR (option)	IR	IR
DAESSY plate	yes (integrated)	yes (default)	option	option	yes (default)	option	option
Rehadapt plate	yes (integrated)	option	option	option	option	–	–
Headphones	yes	yes	–	–	yes	yes	–
Microphone	yes	yes	yes	yes	yes	yes	yes
Scan switch entry	2x	2x	2x	–	2x	2x	2x
Start device with scan switch	yes	yes	yes	–	yes	yes	–

	<b>Tellus (i)6</b>	<b>Tellus (i)5</b>	<b>Vibe 12</b>	<b>Vibe</b>	<b>Mobi 3</b>	<b>Zingui 2</b>	<b>Smart 3</b>
Wake-up from sleep	Touchscreen, switch, eyegaze	Touchscreen, switch, eyegaze (EyeTech only)	Touch (side of device), switch	–	Touchscreen, switch	Touchscreen, switch	On/off button
Eddy / Hey compatible	Hey	Hey Eddy (ME4 only)	Hey	Hey	Hey Eddy (ME4 only)	Eddy	Eddy
Internal phone	-	option	-	-	option	-	-
Bluetooth phone support (*)	SMS calls	SMS calls (supports Jabbla BT app)	SMS calls	SMS calls	SMS calls (supports Jabbla BT app)	SMS + calls (must use Jabbla BT app)	SMS + calls (must use Jabbla BT app)

(\*) Primarily for SMS, choose the 'BlueTooth Smartphone' protocol in the Mind Express *Phone* menu. Phone calls are supported, but will use the speaker of your phone. For ME5 users: iPhones are also supported.

For calls and SMS, choose when available for a bluetooth connection using the Jabbla BT app. This phone app supports Tellus (i)5, Mobi 3, Zingui 2 and Smart 3. Follow these instructions or check the user manual of the device in question to set up the bluetooth connection:

An Android phone v4.2 or higher is required.

1. Start your BlueTooth phone connection in ME 4/5: choose 'Enable BlueTooth' (Smart/Zingui) or "external phone" mode (Mobi 3/Tellus 5) in *Phone* menu.
2. Look for the BlueTooth name in the ME phone menu. Remember it for step 4.
3. Choose 'Connect' in the ME phone menu to enable this ME BlueTooth module.
4. Set up a BlueTooth connection between your phone and this ME BlueTooth module (do not connect with the Windows BlueTooth module!).
5. Install and launch the Jabbla BT app (<https://www.jabbla.com/en/faq/jabbla-bt-app/>) on your phone and configure it to auto connect to your device.

